



MOST COMMONLY ASKED QUESTIONS

CONCEPT 2000

TURNING AN AREA ON OR OFF

Enter your 'CODE' press OK then select 'AREA NUMBER' and press 'ON' or 'OFF'.

IF AN ALARM OCCURS, TURN THE ASSOCIATED AREA OFF

Enter your 'CODE' press OK, select 'AREA NUMBER' and press 'OFF'.

TO ISOLATE OR DE-ISOLATE A ZONE

Enter your 'CODE' press OK then 'MENU', press the Number 3 Key, enter 'ZONE NUMBER' (2 digits) 'OK' then press either 'ON' or 'OFF'

POWER FAILURES / COMMUNICATION REPORTS & GENERAL ALARMS

Turn 'AREA 9' OFF and turn back ON when the problem is rectified. Check with the control room for Communications with them.

TAMPER AREA ALARMS

Turn 'AREA 0' OFF then ON when the condition is rectified. This generally requires the assistance of a technician.

GENERAL INFORMATION

No Closing Signal will be sent unless **ALL** areas are turned ON.
Areas '9' and '0' should NEVER be turned OFF.

Contact the control room on 1300 138 050

24 Hour Emergency Service 0418 955 992.

IF IN DOUBT REFER TO YOUR USER BOOKLET